

APC External Battery Pack

Extended battery backup time for the Back-UPS Pro 1500 VA models

The BR24BPG is an external battery pack that plugs into the rear panel of 1500VA Back-UPS Pro models. Connecting the BR24BP battery pack will approximately triple the normal amount of runtime provided by your standard Back-UPS Pro unit.





Product Features:

- Four 9Ah batteries dramatically extend the runtime of your 1500VA Back-UPS Pro unit. (1500VA Back-UPS Pro models contain two 9Ah batteries standard.)
- Consistent styling with APC's Back-UPS Pro models.
- Recharges automatically via the Back-UPS Pro's internal charger.
- Heavy duty connector plugs securely into the rear panel of the 1500VA Back-UPS Pro.
- Vented, high strength, flame retardant housing provides durability and efficient thermal management.
- 2 year warranty



Rear of BR1500G (sold separately)





BR24BPG Specifications			
Model Number	BR24BPG		
Output			
Output Voltage	12Vdc		
Output Connection	proprietary, non-reversible connector		
Input			
Input Voltage	12Vdc		
Physical			
Unit Dimensions (H x W x D)	11.9 x 4.4 x 15.0" (30.1 x 11.2 x 38.2 cm)		
Unit Weight	29.5 lbs (13.4 kg)		
Shipping Dimensions (H x W x D)	15.0 x 9.0 x 19.0" (381 x 229 x 483 cm)		
Shipping Weight	32.1 lbs (14.6 kg)		
Color	Black		
UPC Code	731304268789		
Compatibility			
The BR24GBP and BR24BP are interchangeable, but their styling and color are significantly different.	Use BR24GBP with: BR1500G (NAM), BR1500-AR (Argentina), BR1500G-BR (Brazil), BR1500G-CN (China), BR1500G-FR (France), BR1500G-GR (Germany), BR1500G-IN (India), BR1500GI (Worldwide) Use BR24BP with: BR1500, BX1500 (NAM), BR1500I (Worldwide)		
Battery			
Expected Life	4 - 6 yrs		
Battery Type	Maintenance-free, sealed lead-acid battery, leakproof		

Approx Runtimes: 1500VA Back-UPS Pro with and without the BR24BPG External Battery Pack

LOAD: <u>Watts / VA</u>	Runtime without the BR24BPG	Runtime with the BR24BPG
50 / 80	157 min	446 min
100 / 160	80 min	232 min
200 / 320	37 min	110 min
300 / 480	22 min	69 min
400 / 640	14 min	49 min
500 / 800	10 min	37 min
600 / 960	7 min	29 min
700 / 1120	5 min	24 min
800 / 1333	4 min	20 min

For more information on runtimes, go to: www.apc.com/sizing

APC by Schneider Electric 132 Fairgrounds Rd West Kingston, RI 02892 Tel: 800-800-4272 www.apc.com

